



FM Systems, Inc.

53 Shelter Hill Road
Plainview, New York 11803
Tel. 516 931-4391 Fax 516 938-2775
www.fm-systems.com

October 4, 1997

Price for this document is FREE the first time, \$50.00 the second time, and \$500.00 the third time you request it.

Time and Date setting on the Panasonic KXTD816 and KDTD1232

Do this at extension 101 with the handset on the hook
Press the PROGRAM button
Then press * # 1234 (you are now in the program mode)
Press "NEXT" 3 times (look on the display for the word "NEXT")
Enter the correct HOURS
Then press the -> (look on the display)
Enter the correct MINUTES
Press AUTO DIAL/STORE
Then press HOLD
Pickup the handset and then hang up to end programming.

Voice Processing System

On your Panasonic Voice Processing System go into mailbox 998 and follow the instructions to change the time.

Intercom – 165 -- #6 ---- * 998 --- 4

Programming the system time:

Press PROGRAM

Press * # 1234 (note: this 1234 is the password. It may be different on you system)

The display should read: SYS-PGM NO ->

Press 000

Press NEXT 2 times

You will see the time. Correct the time and press AUTO DIAL
STORE

Pickup the handset and then hang it up.